



## **Metal Detector**

### BS-500/5


#### Features

- The system has the function of displaying environmental monitoring data.
- · High performance, high sensitivity, high stability.
- · With system networking, can manage multiple devices through one PC.
- Preset metal items weight, volume, size, parts, excluding keys, jewelry, belt buckle and other false alarm.

Comply with EMC electromagnetic radiation standards, use of weak magnetic field technology, heart pacemaker, pregnant women, floppy disk, film, videotape and other harmless.












## **Technical Parameters**

Vertical Dimension	: 2224 x 678 x 125mm
Net weight	: 21kgs (5zones)/24kgs
Gross weight	: 27kgs (5zones)/30kgs
Operating voltage	: AC90V-240V 50/60Hz
Power consumption	: 15W
Operating frequency range	: 1-50 Bands
Operating environment temperature	: -20°C-65°C
Installation environment	: (W) 100cm*(L) 200cm
	(Metal-free minimum range)sheet transverse
Regional detect metal precision range	: Maximum sensitivity 10g Metal
Electrical refer to EN60950 safety standard	: Compliance
Radiation refer to EN50081-1 standard	: Compliance
Anti-interference refer to EN50082-1 standard	: Compliance
Multi-location simultaneous detection and alarm function	: 5 zones
Alarm sound mute mode setting	: Available
Alarm volume adjustable mode	: Available
Multiple alarm sound selection modes	: Available
Infrared start and stop function	: Available

# **BIOROLES**®

# Schematic Diagram of Defense Area





### TechnicalStandard

Compliance
Compliance
Compliance
•
•
•
•

# FunctionalConfiguration

ED display	•
ntegrated four-button panel operation mode	•
ass people statistics function	•
larm statistics function	•
assword protection	•
Multi-location simultaneous detection and alarm function	5/6/9(virtual)zones
etection and intelligent distinction of large items	1
uper brightness patch intelligent partition alarm indicator light	•
lltra- brightness patch double row regions indicator light	•
00 Optional operating frequency bands	•
larm sound mute mode setting	•
larm volume adjustable mode	•
Iultiple alarm sound selection modes	•
nfrared start and stop function	•
ront unilateral location alarm indicator light conversion function	•
he sensitivity of each detection defense zone can be adjusted	•
ach area sensitivity 0-255 adjustable	•
afety level 1-100 optional	•
Multiple quick setup scenarios to choose from	•
lestore factory setting	•

